

RMD69/RMD85型

LCD indicate digital meter



RMD85-22 AC voltage meter



RMD85-50 AC current meter(backlight)



RMD85-40 DC current meter



RMD85-30 DC voltage meter(backlight)



RMD85-40 AC voltage meter

1.Appliance

stable power-supply,regulator,digital instrument,power socket

2.Feature

- clear indicate
- low consumption
- direct read
- high reliability
- competitive price
- high accuracy
- convenient install
- vibration resistance
- anti-interference

3.Main technical index

name items	RMD69-20 RMD85-20 AC voltage meter	RMD69-21 RMD85-21 AC voltage meter	RMD69-22 RMD85-22 AC voltage meter	RMD69-30 RMD85-30 DC voltage meter	RMD69-40 RMD85-40 AC voltage meter	RMD69-50 RMD85-50 DC voltage meter
measure range	50-450V	0-450V	0-1999uV 0-1999mV 0-1.999V 0-19.99V 0-199.9V 0-600V	0-1999uV 0-1999mV 0-1.999V 0-19.99V 0-199.9V 0-600V	0-1999uV 0-1.999mV 0-19.99mV 0-199.9mV 0-5.00A Above 5A with CT or current divider	0-1999uV 0-1.999mV 0-19.99mV 0-199.9mV 0-5.00A Above 5A with current divider
operate power-supply	no need power	AC60 -450V	AC(或 DC)9-12V			
accuracy	0.5±2个字					
max indicate	1999					
screen	LCD display, word height 17.3mm					
measure speed	about 2times per second					
consumption	< 0.1VA(backlight type < 0.2VA)					
shape dimension	RMD69: 86×45×20					
	RMD85: 70×40×20					
install dimension	RDM69:84x43					
	RDM85:68x38					

Note:RMD69,RMD85 type has frequency,voltage frequency combined meter